

5.2.6. Bin settings

At the bin level (storage location) the general and cycle count settings can be defined:

5.2.6.1 General

Organizational structure - Produmex Logex AddOn v19.2.0.2976

Search

Organizational structure

- PMX WMS Demo (ProdumexWMS_D
 - Warehouse 1 (WH_1) - Empty
 - Printer 1 (Printer_1)
 - Printer 2 (Printer_2)
 - TC_RECEP (TC_RECEP)
 - Docks (ZoneDock) - Empty
 - Packing Zone (Zonepacking)
 - Picking Zone (Zonepicking)
 - BinLocation1 (B.001)
 - BinLocation2 (B.002)
 - BinLocation3 (B.003)
 - BinLocation4 (B.004)
 - BinLocation5 (B.005)
 - BinLocation6 (B.006)
 - BinLocation7 (B.007)
 - BinLocation8 (B.008)
 - BinLocation9 (B.009)
 - BinLocation10 (B.010)
 - BinLocation11 (B.011)
 - BinLocation12 (B.012)
 - BinLocation13 (B.013)
 - BinLocation14 (B.014)
 - BinLocation15 (B.015)
 - Production Zone (ZoneProd)

CodeB.001

NameBinLocation1

General

Cycle count

Put away

☒ Active

Location typeFreezer (F1)

☒ Pick location

☐ Priority picking

Sequence400

☐ Can be destination for picking

☐ Block stock from being used for the picking process

☐ Can be lined up

☐ Block move when location is not empty

Max logistic units

Block on different item or batchNone (N)

Quality status

Verification code

☒ Fixed

☐ Can be replenished

Item code	Min quantity	Max quantity	Replenish Qty
DIS_003	100	1000	10

ItemPhoto frame(DIS_003)

Min quantity100

Max quantity1000

Replenish quantity10

Add

Update

Delete

Search

Ok

Cancel

Inventory

Close

Active
Set whether or not the bin is active.

Location type
The user can define a location type (UDT) and link it with a bin location. This information has no technical use, it is for information purposes only.

The location types to be displayed in the drop-down menu can be set in the [Location types \(PMX_LOTY\)](#) user defined table.

Pick location
Set whether or not the bin is a pick location. If this is not the case the items that are stored at this location cannot be used for composing a shipment (order picking). A bin that is not used for picking (=bulk location) can be used to store safety stock that is used to replenish various pick locations.

Priority picking
If the bin location is a pick location, an additional 'Priority picking' checkbox is displayed. When this

checkbox is checked, the bin location has higher priority during stock allocation for pick lists than other bin locations.

Can be destination for picking

Set whether the bin can be a destination for picking. This means that on the pick list it will be possible to select this location as 'dock'.

Sequence

The order in which the products at this location will be used to compose a picking order. The pick locations with the lowest sequence number will be used first to complete the pick order.

Block stock from being used for the picking process

If this setting is enabled, the stock on this location cannot be used to put on a proposal. Also when a pick list gets the allocation on location level, these locations are not taken in account.

Replenishment orders will not take stock from locations with this flag enabled.

The locations with this flag set to true are added to the view

PMX_DISALLOWED_LOCATIONS_FOR_PICKING.

Can be lined up

Set whether or not the bin can be lined up.

Direct consumption of goods (Production manager):

If the option 'Can be lined up' is set to true, this option is visible. By default the lined up locations are not directly consumed when using the production manager (*ProductionReceipt flow*). The stock is locked for the production order, and it is consumed when stopping the production order using the production manager. If this option is set to true, the goods that are lined up on this location, will be automatically consumed on the receipt from production.

Block move when location is not empty.

If this setting is enabled, a move to this location when it is not empty is not allowed.

Block on different item or batch

- None: Nothing will happen.
- Warn: Display a warning message when a different item or a different lot number will be added to that location. This warning is only when using the RF terminals.
- Block: Block the move when a different item or a different lot number will be added to that location.

Max logistic units

The maximum number of allowed logistic units (SSCC's).

If stock is not on an SSCC, the system will regard all this stock as 1 logistic unit.

This will not block a move, but is used when proposing locations on the devices.

Quality status

This option will force a certain quality status on the location.

When adding/moving stock to the location, the system will check whether the quality status of the stock matches with the quality status of the location. If the quality status does not match, the following can happen:

- When booking a move through the handheld device or the Produex inventory report, the system will automatically set the quality status of the stock to the quality status of the location

and then it will perform the move.

- When booking a move with other processes, the system will not change the quality status of the stock and the move will be blocked.

When performing a direct cycle count on a location with a quality status, newly created stock will get this quality status.

How to set up location where only 'released' stock can be stored, but avoid the quality status change when non-released stock is moved on the location

On the [Quality status tab](#) disable the 'Can be put on a pick location' setting for every quality status that is not allowed on the given location. Then enable the pick location setting for the given bin location. Set the reception/quality control area as a non-pick location.

This way only the allowed quality statuses can be stored on pick locations.

Verification code

The verification code is a unique code which can be used for verifying bin locations in the different flows. It has the same function as a bin location code, but it is more complex, and its use is optional.

By default, you can verify the correct bin location on your scanner by scanning the bin location code or entering it manually, in which case an incorrect code may be entered. With a verification code, you can make sure that the correct bin location is verified since verification codes are not shown on the scanner, forcing the user to scan the barcode instead of manually entering the code.

Providing a verification code is optional and you can either use the verification code or the bin location code for verifying the correct bin location in the different flows:

- If a verification code is added to a bin location, you need to verify the bin location by scanning its verification code or scanning its bin location code.
- If no verification code is provided to the bin location, you need to verify the bin location by providing its bin location code.

Please note that a verification code needs to be unique. It cannot be used by another bin, and it cannot be an existing location code. In case you want to add a verification code to more than one bin location, make sure that each bin location has its own, unique verification code. In case you add a verification code which is already used by another bin location, the system will display an error message.

Fixed

Indicates that the storage location is used for specific products. In this case a minimum, maximum quantity is defined for the item on that location.

When a location is fixed, the system will block local moves for other products into that location.

Can be replenished

Enables this option if the bin location can be taken in account for replenishment orders.

A minimum, maximum and replenish quantity needs to be set.

This can only be set when the location is a pick location.

5.2.6.2 Cycle count

Organizational Structure - Produmex Logex AddOn v19.2.0.3027

Search

Code: B.001
Name: BinLocation1

General Cycle count Put away

Cycle counting **Location not counted yet**

☐ Allow location to be counted during cycle count
☐ Allow location to be counted during other operations
☐ Location needs to be counted now

Count after number of days: 0
Count after number of operations: 0
Locked by:
Unlock

Ok Cancel Inventory Close

Allow location to be counted during cycle count

Is the location allowed to be counted?

Allow location to be counted during other operations

Is the location allowed to be counted during other operations? This means that when this location is used on certain flows, the system will check if a count is needed. If so, the system will ask the user to perform a count.

Locations needs to be counted now

When this option is enabled, the location will be counted, regardless of the other settings (Number of days, number of operations, ...)

Count after X days

When a location has not been counted for the number of days defined here, the location needs to be counted. If the number is 0, this setting is not taken in account, and the setting on company level is taken.

Count after X operations

If the number of operations since the last count exceeds the defined number of operations, the location needs to be counted. If the number is 0, this setting is not taken in account and the setting on company level is taken.

Locked by (read-only field)

This field shows the key of the user that is locking the location, because he needs to count the location or is currently in process to count the location.

When a location is locked, it cannot be used in other processes.

The location is released by clicking the 'unlock' button.

Stock on locked locations is not taken in account to create pick list (proposals).

5.2.6.3 Put away

This is used in the functionality 'Location suggestions'

**Item location type**

This can be used to link a location to an item.

An item can also have an item storage location type.

When locations need to be suggested, and an item has a location item type selected, only locations with the same item location type are allowed. The list of item storage location types is stored in the UDT PMX_ISLT.

Put away zones

This stores for a certain storage location:

- What the zones are where the items can be placed
- Or to what put away zone a location belongs to

Put away zone

The put away zone

Sort the pick sequence descending?

Locations belong to a put away zone. How are locations within this zone sorted? Pick sequence descending or ascending?

Location belongs to put away zone?

Does this location belong to a put away zone?

If it is not checked, it means that when goods need to be put away for the current location, the system should look for locations that belong to this zone.

If it is checked, the location belongs to this put away zone.

Sequence number

This is the sequence number for the put away zones. It defines the order in which locations in a put away zone needs to be retrieved.

For more information about the usage see: [Location suggestions](#)

Last update:

2019/04/30 implementation:wms:binsettings <https://wiki.produmex.name/doku.php?id=implementation:wms:binsettings&rev=1556635829>
14:50

From:

<https://wiki.produmex.name/> - **Produmex**

Permanent link:

<https://wiki.produmex.name/doku.php?id=implementation:wms:binsettings&rev=1556635829>

Last update: **2019/04/30 14:50**

